

T2 – Enhanced Lock Programming - Cheat Sheet

Factory Code = 12345

1. **Change Factory code to the new Master code. (Must be 3-5 digits in length.)**

1	2	3	4	5	A _L	1	A _L		A _L		
								<i>(Enter Master Code)</i>		<i>(Re-Enter Master Code)</i>	

2. **Create Manager Codes (Repeat for all 10 managers)** (codes must be 3-5 digits)

Master Code	A _L	00	A _L	
Master Code	A _L	10	A _L	
Master Code	A _L	20	A _L	
Master Code	A _L	30	A _L	
Master Code	A _L	40	A _L	
Master Code	A _L	50	A _L	
Master Code	A _L	60	A _L	
Master Code	A _L	70	A _L	
Master Code	A _L	80	A _L	
Master Code	A _L	90	A _L	
		<i>Manager0-9</i>		<i>(Enter Manager Code)</i>

3. **Add User Codes for Bank 0 (Repeat for banks 0 -9)**

User 01	Master or Manager code	A _L	01	A _L	
User 02	Master or Manager code	A _L	02	A _L	
User 03	Master or Manager code	A _L	03	A _L	
User 04	Master or Manager code	A _L	04	A _L	
User 05	Master or Manager code	A _L	05	A _L	
User 06	Master or Manager code	A _L	06	A _L	
User 07	Master or Manager code	A _L	07	A _L	
User 08	Master or Manager code	A _L	08	A _L	
User 09	Master or Manager code	A _L	09	A _L	
		<i>(Enter User Code)</i>			

4. **1 Time Service Codes**

Master or Manager code	A _L	300	A _L	<i>Clear all Service Codes</i>	
Master or Manager code	A _L	301	A _L		
Master or Manager code	A _L	302	A _L		
Master or Manager code	A _L	303	A _L		
		<i>(Enter User Code)</i>			

5. **Enable Passage Mode**

Master or Manager code	A _L	4	A _L
------------------------	----------------	---	----------------

6. **Disable Passage Mode**

Master or Manager code	A _L	5	A _L
------------------------	----------------	---	----------------

7. **Disable / Enable Banks (Repeat for all banks)**

Master or Manager code	A _L	85		A _L	
Master or Manager code	A _L	84		A _L	
		<i>Bank 0-9</i>			

8. **Silence Keypad**

<i>Master code</i>	<i>AL</i>	223	<i>AL</i>
--------------------	-----------	-----	-----------

9. **Lock Identifier**

<i>Any key</i>	<i>Any key</i>	*	<i>Listen for musical tones</i>
----------------	----------------	---	---------------------------------